


NEW! LANG ALL SOLID STATE COMPACT MIXER



MODEL LMX-2

With exclusive echo feed, the new Lang Solid-State Compact Mixer is the economical approach to all portable and console requirements in any recording or broadcast facility. The LANG Model LMX-2 has 10 inputs—5 each—switchable between high and low level with separate echo feed on each. In addition, the Lang Compact Mixer features a master gain control and a master echo return control. All component circuitry is of plug-in printed circuit design to facilitate customizing to your individual requirements.

FEATURES:

- All Silicon Circuitry • Stainless Steel Control Panel • Plug-in Microphone Pre-Amplifier and Accessory Cards • Separate Echo Feed and Return on each input • Use one, two or more units for multi-channel application

SPECIFICATIONS:

GAIN	97 db max. microphone input 55 db max. line input (17 mv in 0 dbm output)
POWER OUTPUT	Less than 1% thd at +18 dbm
FREQUENCY RESPONSE	±1 db 20-20,000 cps
INPUT IMPEDANCE	Microphone 150 ohms Line 100 K ohms

LOAD IMPEDANCE
NOISE LEVEL

150 or 600 ohms
Equivalent input noise —123 dbm
Output noise —68 dbm with master gain control closed

CONTROLS

POWER SUPPLY
EXTERNAL POWER AVAILABLE
DIMENSIONS
COLOR
WEIGHT
ACCESSORIES

5 mixer, 1 master, 5 echo & 1 echo return 5 Microphone Line selector switches
117 Volts, 60 CPS, 10 Watts
117 Volt AC receptacle on chassis
5¼" H x 19" W x 6¾" D
Stainless Steel Front Panel
10¾ lbs.
Meter panel with 1 to 4 meters
Hammond Reverb Unit
5 Channel Equalizer (plug-in) Model LXQ
Phono Pre-amplifier Card
Tape Head Pre-amplifier Card

LANG ELECTRONICS, INC. 507 FIFTH AVENUE
NEW YORK, N.Y. 10017